

## QBC-5850-6425-70-43S

C-Band, 5.85~6.425GHz, 70dB, 20W (43dBm)

**Features:**

- \* Low Power Consumption
- \* High Power Threshold Setting
- \* Fully Modular Design
- \* Integrated Structural Design

**Applications:**

- \* Satellite Earth Station
- \* Satellite Communication
- \* Telecommunication

### Electrical

RF Frequency:	5.85~6.425GHz
IF Frequency:	950~1525MHz
Output Power (Psat):	20W (43dBm)
Power Consumption:	160W
Small Signal Gain:	70dB
Gain Flatness:	3dB/575MHz, 4dB/875MHz max.
Gain Stability:	3dB max.
Attenuation Control:	0~20dB, step 0.1dB
IM3:	-25dBc
Spurious:	-55dBc
Input/Output VSWR:	1.5/1.35
Phase Noise:	-65dBc/Hz@100Hz -75dBc/Hz@1KHz -85dBc/Hz@10KHz -95dBc/Hz@100KHz
External Reference:	10MHz, 0±5dBm
Supply Voltage:	85~265VAC, 47~63Hz
Impedance:	50Ω

### Environmental

Operating Temperature:	-40~+60°C
Operating Humidity:	0~100%

### Mechanical

IF, Ext.ref. input connector:	50Ω N Female/75Ω F Inch Thread Female
Output Waveguide Size:	WR-137 (BJ70)
Flange:	FDM70
Power Supply:	Aviation socket
Monitor:	Aviation socket (Ethernet port)
Weight:	5Kg

[1] Exclude connectors.

### Outline Drawings

To be done.

Unit: mm [in]

Tolerance: ±0.5mm [±0.02in]

### How To Order

**QBC-5850-6425-70-43S-X**

X: Input connector type

Connector naming rules:

N - N female

F - F Inch Thread female

Examples:

To order a Block Up Converter (BUC), 5.85~6.425GHz, 70dB, 20W (43dBm), N female, specify QBC-5850-6425-70-43S-N.

Customization is available upon request.