

QTF Ultra-Flexible

Features:
* Ultra-Flexible
* Corrosion Resistance

Applications:
* Phased-array Radar
* Laboratory Test
* Small & Complicated Interconnection Occasion

Electrical

Frequency:	DC~26.5GHz
Cut-off Frequency:	35GHz
Impedance:	50Ω
Velocity of Propagation:	76%
Shielding Effectiveness:	90dB min.
Voltage Withstand:	1000V DC
Phase Stability:	1300PPM
Amplitude Stability:	0.15dB/m


Mechanical

Bend Radius (installation):	20.8mm
Bend Radius (repeated):	52.0mm
Weight:	60g/m

Environmental

Temperature:	-55~+85°C
--------------	-----------

Construction



No.	Name	Size (mm)	Material
1	Inner Conductor	1.02	Silver plated copper
2	Dielectric	3.07	Low density PTFE
3	Inner Shield	3.27	Silver-plated copper tape
4	Interlayer	3.55	PTFE
5	Outer Shield	4.12	Silver-plated copper braid
6	Jacket	5.2	PUR

Attenuation & Power Handling

	0.3	0.5	1	3	6	10	12.4	18	26.5
Frequency (GHz)									
Attenuation*1 (dB/100m)	20.5	26.7	38.5	69.8	103.2	139.0	157.9	198.0	252.1
Average Power*2 (W)	280	215	149	82	55	41	36	29	23

[1] VSWR:1.0; Ambient: +25°C (77°F)

[2] VSWR:1.0; Ambient: +40°C (104°F); Sea level

Calculate Cable Attenuation: Attenuation (dB/100m) = 1.136600 * √F (MHz) + 0.002530 * F (MHz)

Calculate Connector Attenuation: Attenuation (dB) = 0.03 * √F (GHz)

How To Order

QTF-X-Y-Z

X: Frequency in GHz
Y: Connector type
Z: Length in meters

Examples:

To order a QTF cable assembly, DC-18GHz, SMA male to SMA female, 0.5 meter, specify QTF-18-SSF-0.5.

Connector naming rules:

S - SMA (26.5GHz, VSWR 1.3)

N - N (18GHz, VSWR 1.3)

Female Connector - Add 'F' after connector name

Right Angle - Add 'R' after connector name (VSWR increase 0.1)

QTF Mating Connector

QCS-MG-Z500W-1

SMA male, Stainless steel

QCN-MG-Z500W-1

N male, Stainless steel

QCS-FG-Z500W-1

SMA female, Stainless steel