

QCK-N-6-2

N Connectors, DC~6GHz, Economic Type

Features:
* High Precision

Applications:
* Calibration
* Laboratory Test



Description

With the components in these kits you can make error-corrected measurements of devices supplied with N connectors from DC to 6 GHz.

Components

Part Number	Description	Frequency	Impedance	VSWR	Phase Accuracy	Inner Conductor	Outer Conductor	Size	
		(GHz)	(Ω)	(Max.)	($^{\circ}$, Max.)			(mm)	
QONC-M-6-2	N male open	DC~6	50	-	± 1	Without inner conductor	Passivated stainless steel	-	
QONC-F-6-2	N female open					Gold plated beryllium copper		-	
QSNC-M-6-2	N male short			-	± 1	Passivated stainless steel		-	
QSNC-F-6-2	N female short					Gold plated beryllium			-
QCT-N-C-M-6-2	N male termination			1.035	-	Gold plated beryllium		-	
QCT-N-C-F-6-2	N female termination					m copper			-
QW-N1-CK	N torque wrench			-	-	Nickel plated tool steel (Head)		Aluminium, anodised (Handle)	19.1 (Opening size)
QANNC-MM-2*	N male to N male adapter			1.05	-	Gold plated beryllium		Passivated stainless steel	-
QANNC-MF-2*	N male to N female adapter								
QANNC-FF-2*	N female to N female adapter								
Storage Box		-	-	-	-	Wood	275*200*80/ 145*145*60		

“*” Equal phase adapter

How To Order

QCK-N-6-2-10 All the 10 components in one box.

QCK-N-6-2-3M Three in one box, including open, short and termination, male, QONC-M-6-2, QSNC-M-6-2, QCT-N-C-M-6-2.

QCK-N-6-2-3F Three in one box, including open, short and termination, female, QONC-F-6-2, QSNC-F-6-2, QCT-N-C-F-6-2.

QCK-N-6-2-6 Six in one box, including QCK-N-6-2-3M and QCK-N-6-2-3F.

To order a single component, specify the npart umber in the first column.