

2-Way Power Divider/Combiner

QPD2-900-1300-K1-N 2-Way, 0.9~1.3GHz

Features: * Small Size

- - Applications: * Amplifiers
- * Low Insertion Loss
- * Mixers
- * Antennas
- * Laboratory Test


Electrical

Frequency:	0.9~1.3GHz
Insertion Loss:	0.5dB max.
VSWR:	1.25 max.
Isolation:	20dB min.
Amplitude Balance:	0.1dB max.
Phase Balance:	3° max.
Power @SUM Port:	100W as divider
	100W as combiner

Mechanical

Size ^{*1} :	60*80*30mm
	2.362*3.15*1.18in
Connectors:	N Female
Mounting:	4-Φ3.2mm through-hole
[1] Exclude connectors.	

Outline Drawings



Unit: mm [in] Tolerance: ±0.5mm [±0.02in]

How To Order QPD2-900-1300-K1-N

Customization is available upon request.