



# QPD8-20-100-K15-S

8-Way, 0.02~0.1GHz

Features:
\* Small Size
\* Low Insertion Loss

Applications:
\* Amplifiers
\* Mixers
\* Antennas

\* Laboratory Test

#### **Electrical**

Frequency: 0.02~0.1GHz
Insertion Loss: 1.3dB max.

VSWR: 1.5 max.
Isolation: 20dB min.

Amplitude Balance: ±0.2dB

Phase Balance: ±5°

Power @SUM Port: 150W as divider

150W as combiner

#### Mechanical

Size\*1: 164\*126\*26mm


6.457\*4.961\*1.024in

Connectors: SMA Female

Mounting: 4-Φ4.5mm through-hole

[1] Exclude connectors.

## **Outline Drawings**



Unit: mm [in]

Tolerance: ±0.5mm [±0.02in]

### **How To Order**

QPD8-20-100-K15-S

Customization is available upon request.