



QDB-0.3-140000-88F

300KHz~140GHz

Features:
* Broadband
* Low VSWR

Applications: * Telecom

* Instrumentation

* Laboratory Test

* Radar

Electrical

Frequency Range: 300KHz~140GHz

Insertion Loss: 2.5dB typ. VSWR: 1.8 typ.

Voltage: 16V typ.
Power: 1W typ.
Impedance: 50Ω

Mechanical

Connectors: 0.8mm

Housing: Gold plated brass


Type: Inner

How To Order

QDB-0.3-140000-88F

Customization is available upon request.

Outline Drawings



Unit: mm [in]

Tolerance: ±0.2mm [±0.008in]